

S45AU MOBILE MIST CANNON



Designed &
Manufactured
in
Australia



FEATURES

- Our Unique S45AU has no water tank, can be positioned on water trucks or positioned where a larger cannon would not work
- 45-Meter mist throw
- 18-L/PM high-pressure mist pump
- Cannon can oscillate 330° with adjustable end points
- Cannon can be raised up to 45°
- Powered by a Honda/Makinox 16kVA Petrol Generator
- Has forklift slippers down the length of the base plate
- Heavy duty design makes this perfect for harsh conditions
- Our smallest mist cannon yet makes this machine perfect for applications like Mines, Quarries, Tunnels, Factories or Events

S45AU MOBILE MIST CANNON



1. STOP BUTTON
2. NO WATER SIGNAL LIGHT
3. MANUAL FAN ADJUST LEFT & RIGHT
4. REMOTE CONTROL & MANUAL OPERATION SWITCH
5. FAN ON/OFF SWITCH (GIVE 15SEC BEFORE TURNING ON MIST)
6. MIST CONTROL ON/OFF
7. OSCILLATION ON/OFF SWITCH
8. MANUAL FAN ADJUST UP/DOWN
9. KEY LOCK TO OPEN CABINET
10. LINAK ACTUATOR TO LIFT CANNON
11. TRAVEL LATCH
12. DUAL EXTERNAL FILTERS 10 & 5 MICRON
13. HIGH & LOW PRESSURE GAUGES
14. LATCH TO ACCESS HIGH-PRESSURE PUMP IN TURRET BOX
15. FORKLIFT LIFT POINT
16. TRAVEL LATCH IN LOCKED POSITION
17. PROXIMITY SENSORS FOR OSCILLATION
18. GENERATOR TRIP SWITCHES
19. ELECTRICAL PLUGS (1 X 32A 3PHASE - 2 X 1A 1PHASE)
20. FUEL CAP FOR PETROL ONLY
21. DUAL MISTING RING TOTAL 60 NOZZLES

DIMENSIONS:

Length: 1800mm
Width: 1200mm
Height: 1500mm

WATER TANK CAPACITY:

nil

WEIGHT:

(Dry Weight plus Generator)

Dry Weight: 580kg

FLOW RATE:

18 L/min of Mist per minute.

TRANSPORT:

The bed is fitted with Fork interface on the long edge.

GENERATOR:

16kVA Honda /
Makinex Electric
Start Generator
1 x 32A 3-Phase Port
2 x 240V 15A Ports

To run the Non-Generator
version you will require a
20 Amp 3-phase plug

WANT TO KNOW MORE?

Call one of our friendly
& knowledgeable team
members today.